

Comparison Chart

Using the chart below find the correct encoder or decoder that you need. Please feel free to contact us if you require further assistance.
E: sales@antrica.com | T: +44 (0) 1628 626 098



Comparison Chart

Using the chart below find the correct encoder or decoder that you need. Please feel free to contact us if you require further assistance.
E: sales@antrica.com | T: +44 (0) 1628 626 098



Product	Encoder	Decoder	ONVIF Compliant	Hardware to Hardware Latency mS	Hardware to Software Latency mS	Max Resolution	Max Frame Rate/Frame/sec	Max Data Rate Mbits/s	Unicast / Multicast	RTSP	MPEG-TS	RTMP	HTTP Streaming	Browser Video Stream Viewing	VLC Video Stream Viewing	Dedicated Viewing Software	HDMI	DVI-D using HDMI to DVI Cable	HD-SDI	Component via VGA Dongle	Composite PAL NTSC	Independent Video Channels	Streams	Audio Format	Two Way Audio	Embedded Audio Support	Analogue Audio Support	SD or USB Local Recording	RS232	RS485	PoE or USB	Power Supply DC Volts	Main Features		
Encoders / Decoders(Dual Use or pairs)																																			
ANT-3300	✓	✓	✓	250	350	720x576	30	8	✓	✓	✓	✗	✗	✓	✓	✓	✗	✗	✗	✗	✓	1	2	AAC G711	✓	✗	✓	✓	✓	✓	✓	P	12	SD Encoder Decoder with Inputs and outputs for monitoring	
ANT-32000A	✓	✓	✓	350	450	1920x1080	30	8	✓	✓	✓	✗	✗	✓	✓	✓	✓	✓	✗	✗	✓	1	2	AAC G711	✓	✗	✓	✓	✓	✓	✓	P	12	HD and SD Encoder Decoder with HDMI and Composite In/Out	
ANT-32000AS	✓	✓	✓	350	450	1920x1080	30	8	✓	✓	✓	✗	✗	✓	✓	✓	✓	✓	✓	✗	✓	1	2	AAC G711	✓	✗	✓	✓	✓	✓	✓	P	12	HD and SD Encoder Decoder with HD-SDI HDMI and Composite	
ANT-4000E	✓	✗	✗	<100	200	1920x1080	60	12	✓	✓	✓	✗	✗	✗	✓	✗	✓	✓	✓	✓	✓	1	1	44.1/48kHz	✗	✓	✓	✗	✗	✗	✗	✗	12	Low Latency HDMI DVI over IP encoder	
ANT-4000D	✗	✓	✗	<100	200	1920x1080	60	12	✓	✓	✓	✗	✗	✗	✓	✗	✓	✓	✓	✓	✓	1	1	44.1/48kHz	✗	✓	✓	✗	✗	✗	✗	✗	12	Low latency HDMI DVI VGA Decoder when used with ANT-4000E	
ANT-6000E	✓	✗	✗	<100	200	1920x1080	60	25	✓	✓	✓	✗	✗	✗	✓	✗	✓	✓	✓	✓	✗	1	1	44.1/48kHz	✓	✓	✓	✗	✓	✓	✓	P	12	Low Latency 3G HD-SDI encoder with HDMI VGA	
ANT-6000D	✗	✓	✗	<100	200	1920x1080	60	25	✓	✓	✓	✗	✗	✗	✓	✗	✓	✓	✓	✓	✗	1	1	44.1/48kHz	✓	✓	✓	✗	✓	✓	✓	P	12	Low Latency Decoder when used with ANT-6000E	
ANT-1771	✓	✓	✗	<100	100	1920x1080	30	25	✓	✓	✓	✗	✗	✗	✓	✗	✗	✗	✗	✗	✓	4	4	44.1/48kHz	✗	✗	✓	✓	✓	✓	✓	✗	12	Ultra small multi channel Encoder Decoder for UAV applications	
ANT-1772	✓	✓	✗	<100	100	1920x1080	30	25	✓	✓	✓	✗	✗	✗	✓	✓	✓	✗	✓	✗	✓	P	✓	44.1/48kHz	✗	✗	✓	✓	✓	✓	✓	✗	12	Ultra small multi channel Encoder Decoder for UAV applications	
ANT-1773	✓	✓	✗	<100	100	1920x1080	30	25	✓	✓	✓	✗	✗	✗	✓	✓	✓	✗	✓	✗	✓	P	✓	44.1/48kHz	✗	✗	✓	✓	✓	✓	✓	✗	12	Ultra small multi channel Encoder Decoder for UAV applications	
ANT-45000	✓	✓	✓	350	450	1920x1080	60	16	✓	✓	✓	✓	✗	✓	✓	✓	✓	✓	✓	✗	✓	1	4	AAC G711	✓	✓	✓	✓	✓	✓	✓	✓	✓	12	HD Encoder or Decoder with 3G-HD-SDI HDMI Inputs or Outputs
Encoders Only																																			
ANT-3410	✓	✗	✓	250	350	720x576	30	8	✓	✓	✓	✗	✗	✓	✓	✓	✗	✗	✗	✗	✓	4	8	AAC G711	✓	✗	✓	✓	✓	✓	✓	P	12	4 Ch SD encoder with Quad view output via Composite	
ANT-35000	✓	✗	✓	350	450	1920x1080	60	16	✓	✓	✓	✓	✗	✓	✓	✓	✓	✓	✓	✗	✓	1	4	AAC G711	✓	✓	✓	✓	✓	✓	✓	✓	P	12	HD and SD Encoder only with 3G HD-SDI HDMI and Composite In/Out
ANT-38000	✓	✗	✓	350	450	4096x2160 3840x2160	24 30	16	✓	✓	✓	✗	✗	✓	✓	✓	✓	✓	✓	✗	✓	1	4	AAC G711	✓	✓	✓	✓	✓	✓	✓	✓	✓	12	4K HD and SD Encoder only with 3G HD-SDI HDMI
ANT-2000	✓	✗	✓	350	450	1920x1080	60	20	✓	✓	✓	✓	✓	✓	✓	✗	✓	✓	✗	✗	✗	1	2	MP3 G711	✗	✓	✓	✗	✗	✗	✗	✗	12	HD Encoder 1CH with HDMI input HDCP	
ANT-2004	✓	✗	✓	350	450	1920x1080	60	20	✓	✓	✓	✓	✓	✓	✓	✗	✓	✓	✗	✗	✗	1	2	MP3 G711	✗	✓	✓	✗	✗	✗	✗	✗	12	HD Encoder 4CH with HDMI input HDCP	
ANT-7300	✓	✗	✗	x	150	1920x1080	60	40	✓	✓	✗	✗	✗	✗	✓	✗	✓	✓	✗	✗	✗	1	1	44.1/48kHz	✗	✓	✗	✗	✗	✗	✗	U	12	Keyboard Video and mouse over IP at 1080P60 at less than 30 Mbits/s	
Decoders Only																																			
ANT-36000	✗	✓	✓	450	NA	1920x1080	60	16	✓	✓	✓	✗	✗	✓	✓	✓	✓	✓	✓	✗	✓	1	100	AAC G711	✓	✓	✓	✓	✓	✓	✓	✓	✓	12	HD and SD Decoder with HD-SDI HDMI and Composite outputs
Spotbox4k	✗	✓	✓	350	450	3840 x 2160	30	12	✓	✓	✓	✗	✓	✓	✓	✗	✓	✓	✗	✗	✗	1	16	N/A	✗	✗	✗	✓	✗	✗	✗	5	16 Channel Decoder with 4K display Quad/Single plus Remote control		