

## ANT-4000E/D Firmware Upgrade

• Open Internet Explorer and type in the URL box the IP address of the Encoder (192.168.0.151) or Decoder (192.168.0.152)

[] 192.168.0.152/

· In the left navigation column select "S/W Image"

Navigation	System Configuration	
System Configuration	Ethernet IP	192.168.0.152
Serial Port Configuration	Ethernet NetMask	255.255.255.0
S/W Images Streaming Control	Ethernet MAC	00:06:29:32:22:22
Save Changes Reboot System	Gateway	192.168.0.1
	Streaming Mode	Multicast V
	Group IP(multica:	st) 227.2.2.7
	Peer IP(lan)	192.168.0.151
	Submit Refres	h LedTest

• In "Select Local file" URL box select Browse and point towards your updated firmware image.

Navigation	S/W Images		
System Configuration	Working S/W barco:203.36		
S/W Images	downloaded S/W		
Save Changes	Server file's URL		Download
<sup>≝</sup> Reboot System	Select Local file	Browse	Upload
	Once you click the "Upload" butt refresh the browser till web is ref Refresh	on, DO NOT TOUCH any brows reshed automatically.	er buttons and

• Then click "**Upload**" and a message "write to flash" will come up, select this button when prompted to save your updated firmware.