

ANT-35000 series encoders upgrade guide

1. Open web page & Click "Setup"



2. Click "system"

| | / | | | | | | | |
|---------------------------------------|---|----------------------|---------------|-----------|------------|-------------|-----------|-------------|
| Video&Audio | - | Video | | | | | | |
| 🛊 Image | + | | Enable | Algorithm | Resolution | Bitrate | Framerate | |
| Network | + | Primary Encoding | On | H.264 | 1920x1080 | 1639 (kbps) | 25 (fps) | |
| Event | + | Secondary#1 Encoding | Off | N/A | N/A | 0 (kbps) | 0 (fps) | |
| D Record | + | Secondary#2 Encoding | Off | N/A | N/A | 0 (kbps) | 0 (fps) | |
| Device | + | Secondary#3 Encoding | Off | N/A | N/A | 0 (kbps) | 0 (fps) | |
| PTZ | + | 2500 | | | | | | Primanu |
| & User | + | 2020-00-0 | | | | | | Secondary#1 |
| System | - | 2000 | $/ \setminus$ | | |) | | Secondary#2 |
| Information | | 1500 | | | | | | Secondary#3 |
| Upgrade&Reboo | t | | | | | | | |
| Time | | 1000 | | | | | | |
| - OSD | | | | | | | | |
| Language | | 500 | | | | | | |
| - Log | | | | | | | | |

For further help and advice please contact Antrica on: Email: <u>support@antrica.com</u> Phone: +44 1628 626098 ext 3

Document info

| Version | date | author | Comments |
|---------|-----------|---------|------------------|
| 1.0 | 9-Dec-19 | David M | Initial |
| 1.1 | 30-Oct-20 | David M | Typo corrections |
| | | | |



3. Click "Upgrade&Reboot"

| | | Live |
|-------------------|-------------------------------|------------------|
| 😼 Video&Audio 🛛 + | Firmware | |
| 🙀 Image 🛛 + | Version <u>V3.907R01_T913</u> | |
| 🙀 Network 🛛 🕂 | Upgrade Browse | Firmware Upgrade |
| 🖬 Event + | | |
| TRecord + | Config Backup&Restore | |
| 🔜 Device | Backup | Config Backup |
| 📩 PTZ 🛛 + | Restore Browse | Config Restore |
| 😢 User 🛛 🔸 | | oring restore |
| 👌 System 🛛 – | Reboot | |
| Information | | Reboot |
| Upgrade&Reboot | | |

4. Click "Browse" and navigate to the required .tus file

| r i i i i i i i i i i i i i i i i i i i | | 1125 | • 💷 🕜 |
|---|---|---|--|
| Name | Size | Туре | Date modified |
| archived Firmware | | File folder | 03/10/2019 10 |
| Product A1 Updates - NEW 1DMI CHIP.pdf | 78 KB | Adobe Acro | 11/04/2018 14 |
| J V3.907R01_antrica.tus | 38,301 KB | TUS File | 27/09/2019 0 |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | Name Archived Firmware Product A1 Updates - NEWHDMI CHIP.pdf V3.907R01_antrica.tus | Name Size Archived Firmware Product A1 Updates - NEW ADMI CHIP.pdf 78 KB V3.907R01_antrica.tus 38,301 KB | Name Size Type Archived Firmware File folder Product A1 Updates - NEW HDMI CHIP.pdf 78 KB Adobe Acro V3.907R01_antrica.tus 38,301 KB TUS File |

- 5. Select file then click "Open"
- 6. Click "Firmware Upgrade"

| | | | Live |
|---------------|---|--|------------------|
| 5 Video&Audio | + | Firmware | |
| 📄 Image | + | Version V3.907R01_T913 | |
| Setwork | + | Upgrade C:\Users\work pc\Dropbo Browse | Firmware Upgrade |
| 🐻 Event | + | | |





8. Wait for the firmware to download to encoder

| | | | | Live |
|---------------------------------|---|-----------|--|------------------|
| 5 Video&Audio | + | Firmware | | |
| 📑 Image | + | | Version <u>V3.907R01_T913</u> | |
| Setwork | + | | Upgrade C:\Users\work pc\Dropbo Browse | Firmware Upgrade |
| Event | + | | | |
| Record | + | Config Ba | ackup&Restore | |
| 🛄 Device | + | | Backup | Config Backup |
| 📥 PTZ | + | | File Downloading 🗙 | Confin Restore |
| & User | + | | Now Downloading Please wait | Somig Restore |
| 는 System | - | Reboot | | |
| Information | | | | Reboot |
| Upgrade&Reboot | | | | |
| - Time | | Factory R | leset | |

9. The firmware is then installed, when progress bar is all blue encoder will reboot

| 🧟 AntricaInfo_02 | × 🧟 Firmware Upgrade Process | × 📑 |
|---------------------------|------------------------------|-----|
| File Edit View Favourites | Tools Help | |
| Now, Upgrading Plea | se wait a minute. | |
| | | |
| | | |

10. The encoder will then reboot and the web page will reappear

| Video&Audio | + | Firmware | |
|---------------------------------|---|------------------------|------------------|
| 🛉 Image | + | Version V3.907R01_T913 | |
| Network | + | Upgrade Browse | Firmware Upgrade |
| Event | + | | |
|] Record | + | Config Backup&Restore | |
| Device | + | Backup | Config Backup |
| PTZ | + | Restore Browse | Config Restore |
| 👌 User | + | | |
| System | - | Reboot | |
| Information | | | |