



# 1773 Setup to play two Unicast streams to a PC with VLC player

PC IP is 192.168.0.18

Ports are 1234 and 1235

IP of ANT-1773 is on same  
subnet as PC

192.168.0.xxx

# First Check CSI1 and CSI2

---

## System

Config Number: **CFG 1**

Operation State: **Operational**

USB to Disk: **Disable**

Camera CSI1: **tw9910**

Camera CSI2: **hdspi**

[Setup Generic Camera](#)

[Setup Analog Camera](#)

[Setup External Sync](#)

[Control UART](#)

[Network](#)

---

# Next Check i Info page Both should be locked if using HD and SD

68.0.30

## Info

### SW Info

Build Date: Mar 23 2017 14:27:56  
libudvpdvr.so: 2.9.4.7  
LDVC: 2.3.5.3  
FPGA: Unknown

### **eth0**

IP Address: 192.168.0.30  
MAC Address: 0a:1b:dd:2a:23:dd


### Camera

	Name	Status	Resolution	Interlaced	FPS
	SD1	Lock	PAL	Interlaced	25
	SD2	Not Exist	Unknown	Unknown	0
	SD3	Not Exist	Unknown	Unknown	0
	SD4	Not Exist	Unknown	Unknown	0
	HD1	Not Exist	Unknown	Unknown	0
	HD2	Lock	1920x1080	Noninterlaced	30
	SD5	Not Exist	Unknown	Unknown	0
	SD6	Not Exist	Unknown	Unknown	0
	SD7	Not Exist	Unknown	Unknown	0
	SD8	Not Exist	Unknown	Unknown	0


### Storage

Storage    Total Size    Used Space    Format



 Product photos


# Setup Streaming



- Mux1      Unicast/TS/192.168.0.18/1234
- Mux2      Unicast/TS/192.168.0.18/1235
- Mux3      Unicast/TS/192.168.0.1/1237
- Mux4      Unicast/RTSP




Setup Streaming- add the IP address  
of computer using VLC player and  
choose a port  
192.168.0.18 is PC IP



# Streaming


To start streaming the Green triangle must be a RED square




- Mux1      Unicast/TS/192.168.0.18/1234
- Mux2      Unicast/TS/192.168.0.18/1235
- Mux3      Unicast/TS/192.168.0.1/1237
- Mux4      Unicast/RTSP



In VLC Player type  
udp://@:1235  
(PC Ip address is 192.168.0.18 in  
this example)



# Streams will play One HSD and other SD using different Ports 1234 and 1235



- Mux1      Unicast/TS/192.168.0.18/1234
- Mux2      Unicast/TS/192.168.0.18/1235
- Mux3      Unicast/TS/192.168.0.1/1237
- Mux4      Unicast/RTSP

